

USB To RS-422 / 485 Converter

US-101-485



- USB
 - ✧ Chipset : Silicon Laboratories CP2102
 - ✧ Compliant : USB 1.0 , 1.1 , 2.0
 - ✧ Connector : USB type A
 - ✧ Baud Rates : Full speed 12 Mbps
- Serial Port
 - ✧ Port : 1 port (Terminal Block)
 - ✧ RS-422 : RxD+ , RxD- , TxD+ , TxD- ,
 - ✧ RS-485 : Data+ , Data-
 - ✧ RS-422 , RS-485 Auto Detect
 - ✧ RS-422 , RS-485 Surge Protect
 - ✧ Receive buffer : 576 Byte
 - ✧ Transmit buffer : 640 Byte
 - ✧ Baud Rate : 300 ~ 230.4 K bps
 - ✧ Flow Control : X-On / X-Off or Hardware
- Driver Support
 - ✧ Windows -98SE / 2000 / XP / Server 2003 / Mac osx / os9 / Linux 2.4 / 2.6
- Power : USB Bus Power (5V)
- Dimension
 - ✧ Size : 55 * 40 * 25 mm (W * D * H)
 - ✧ Weight : 35 gm
- Environment
 - ✧ Operating Temp : 0~60°C
 - ✧ Storage Temp : -20 to 85°C
 - ✧ Humidity : 5~95 % RH

